SMALL SIGNAL SCHOTTKY BARRIER DIODES

FEATURES:

- Low ForwardVoltage drop
- Fast Switching
- Ultra-small Surface MountPackage

MECHANICAL DATA


Case: SOD-323 plastic Polarity: Cathode band


Leads: Solderable per MIL-STD-202,

Method 208

Weight: 0.004 grams

SOD-323





Dimensions in inches and (millimeters)

MAXIMUM RATINGS AND ELECTRICAL CHARACTERISTICS

Rating at 25° C ambient temperature unless otherwise specified.

Single phase half wave, 60 Hz resistive or inductive load.

For capacitive load, derate current by 20%.


Characteristic	Symbol	BAT42WS	BAT43WS	Units
Maximum recurrent peak reverse voltage	V _{RRM}	30	30	Volts
Maximum RMS voltage	V _{RMS}	21	21	Volts
Maximum DC blocking voltage	V_{DC}	30	30	Volts
Maximum average forward rectified current at Ta=25 $^{\circ}\mathrm{C}$	I _(AV)	0.1		Amps
Peak forwardsurge current 10ms single half sine-wave superimposed on rated load (JEDEC Method)	I _{FSM}	4		Amps
Both Types IF=0.2A Maximum instantaneous forward voltage Both Types IF=0.2A IF=0.01A IF=0.05A IF=0.002A IF=0.002A IF=0.015A	VF	0.40 0.65	0.33 0.45	Volts
Power dissipation	PD	200		mW
	l In	0.5 100		μΑ
Minixmum reversebreakdown voltage IR=100uA	V(BR)R	30		Volts
Typical reverserecovery time (NOTE 1)	T _{RR}	5.0		nS
Total capacitance (NOTE 3)	C _T	10		P _F
Operating and Storage temperature range	T _J ,T _{Stg}	-65to+125		$^{\circ}$ C


NOTES:


(1) Reverse Recovery Test CONDITION: $I_F = I_R = 0.01A$, $I_{RR} = 0.25A$


(3)VR=1.0V,f=1.0MHZ


RATINGS AND CHARACTERISTIC CURVES











March 2020

BAT42WS THRU BAT43WS

Disclaimer

DACO Semiconductor reserve the right to make modifications, enhancements, improvements, corrections or other changes without further notice to this document and any product described herein.

DACO Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does DACO Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages.

Purchasers is responsible for its products and applications using DACO Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by DACO Semiconductor. "Typical" parameters which may be provided in DACO Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts.

DACO Semiconductor products are not designed, authorized or warranted to be suitable for use in life support, life-critical or safety-critical systems or equipment, nor in applications where failure or malfunction of DACO Semiconductor's product can reasonably be expected to result in personal injury, death or severe property or environmental damage. DACO Semiconductor accept no liability for inclusion and/or use of DACO Semiconductor's products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

Purchasers buy or use DACO Semiconductor products for any such unintended or unauthorized application, Purchasers shall indemnify and hold DACO Semiconductor and its suppliers and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that DACO Semiconductor was negligent regarding the design or manufacture of the part.

No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written permission of DACO Semiconductor Co., Ltd.

March 2020