

**KBPC15005T/W** THRU KBPC1510T/W

1.135(28.8)

1.115(28.3)

# SINGLE PHASE SILICON BRIDGE RECTIFIER

#### FEATURES:

- High efficiency
- Silicon junction
- Metal case
- Rating to 1000 V PRV

MECHANICAL DATA

Polarity : As marked on case

Mounting : Hole for #10 screw

Case : Mounted in the bridge encapsulation

#### 0.732(18.6) 0.200(5.08) 0.692(17.6) **KBPC-W** DIA 1 13<u>5(28.8)</u> 0.732(18.6) 1.115(28.3) 0.692(17.6) 1 0.470(11.9) 0.430(10.9) Hold for #10 Screw 0.220(5.59) 1.135(28.8) 1.115(28.3) 0.672(17.1) 0.200(5.08) **KBPC-T** DIA 0.632(16.1) ∄ t t <u>1 135(28.8)</u> 0.672(17.1) 0.582(14.8) 1.115(28.3) 0.632(16.1) 0.542(13.8) 0.732(18.6) 0.692(17.6)

Hold for

#10 Screw

0.220(5.59)

Dimensions in inches and (millimeters)

#### MAXIMUM RATINGS AND ELECTRICAL CHARACTERISTICS

Rating at 25° C ambient temperature unless otherwise specified. Single phase half wave, 60 Hz resistive or inductive load. For capacitive load. derate current by 20%.

Characteristic	Symbol	КВРС							
		15005 T/W	1501 T/W	1502 T/W	1504 T/W	1506 T/W	1508 T/W	1510 T/W	Units
	Marking	KBPC 15005	KBPC 1501	KBCP 1502	KBPC 1504	KBPC 1506	KBPC 1508	KBPC 1510	
Maximum recurrent peak reverse voltage	V <sub>RRM</sub>	50	100	200	400	600	800	1000	Volts
Maximum RMS voltage	V <sub>RMS</sub>	35	70	140	280	420	560	700	Volts
Maximum DC blocking voltage	V <sub>DC</sub>	50	100	200	400	600	800	1000	Volts
Maximum average forward rectified current at Tc=55 $^\circ\! C$	Ιo	15						Amps	
Peak forward surge current 8.3ms single half sine-wave superimposed on rated load (JEDEC Method)Per leg	I <sub>FSM</sub>	300						Amps	
Maximum instantaneous forward voltage Per leg IF=7.5A	VF	1.1							Volts
Maximum DC reverse current $Tc = 25^{\circ}C$ at rated DC blocking voltage Per leg $Tc = 100^{\circ}C$	I <sub>R</sub>	5.0 500							μΑ
Typical thermal resistance (NOTE1)	R <sub>th</sub> -JC	2.3							°C/W
Typical junction capacitance (NOTE2)	СJ	300							P <sub>F</sub>
Operating junction and Storage temperature range	Tj, Tstg	-55to+150							°C

NOTES:


(1) Device mounted on 300mm x 300mm x 1.6mm cu Plate Heaksink


(2) Measured at 1MHZ and applied reverse voltage of 4.0V D.C.





## KBPC15005T/W THRU KBPC1510T/W


### RATINGS AND CHARACTERISTIC CURVES












www.dacosemi.com.tw




## KBPC15005T/W THRU KBPC1510T/W

#### RATINGS AND CHARACTERISTIC CURVES



Dimensions in Inches and (millimeters)







## Disclaimer

DACO Semiconductor reserve the right to make modifications, enhancements, improvements, corrections or other changes without further notice to this document and any product described herein.

DACO Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does DACO Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages.

Purchasers is responsible for its products and applications using DACO Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by DACO Semiconductor. "Typical" parameters which may be provided in DACO Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts.

DACO Semiconductor products are not designed, authorized or warranted to be suitable for use in life support, life-critical or safety-critical systems or equipment, nor in applications where failure or malfunction of DACO Semiconductor's product can reasonably be expected to result in personal injury, death or severe property or environmental damage. DACO Semiconductor accept no liability for inclusion and/or use of DACO Semiconductor's products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

Purchasers buy or use DACO Semiconductor products for any such unintended or unauthorized application, Purchasers shall indemnify and hold DACO Semiconductor and its suppliers and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that DACO Semiconductor was negligent regarding the design or manufacture of the part.

No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written permission of DACO Semiconductor Co., Ltd.