SINGLE PHASE GLASS PASSIVATED BRIDGE RECTIFIERS

FEATURES:

- Integrally molded heat sink provide low thermal resistance for max, heat dissipation
- High surge current capability
- Universal 3-way terminals: snap on, wire-around, or P.C. board mounting
- High temperature soldering guaranteed:
 260° C/10 seconds at 5lbs. (2.3kg)tension
- Al plate plastic case

MECHANICAL DATA

Case: Molded plastic with heat-sink integrally mounted in the bridge encapsulation
Terminals: Either nickel plated 0.25". Faston lugs or

copper leads 0.040"diameter sufficient letter"W" added to indicate leads


Polarity: Polarity symbols marked on body


Mounting Position: Bolt down on heat-sink with silicone

thermal compound between bridge

and mounting surface

Weight: 15 grams or 0.53 ounce Mounting Torque: 20 in.-lb. max





Dimensions in inches and (millimeters)


MAXIMUM RATINGS AND ELECTRICAL CHARACTERISTICS


Rating at 25° C ambient temp. unless otherwise specified. Single phase, half sine wave, 60 Hz, resistive or inductive load. For capacitive load, derate current by 20 %.

	Symbol	GBPC							
Characteristic		35005 T/W	3501 T/W	3502 T/W	3504 T/W	3506 T/W	3508 T/W	3510 T/W	
	Marking	GBPC 35005	GBPC 3501	GBPC 3502	GBPC 3504	GBPC 3506	GBPC 3508	GBPC 3510	Units
Maximum recurrent peak reverse voltage	Vrrm	50	100	200	400	600	800	1000	Volts
Maximum RMS voltage	VRMS	35	70	140	280	420	560	700	Volts
Maximum DC blocking voltage	VDC	50	100	200	400	600	800	1000	Volts
Maximum average forward rectified current at TC=50 ° C	lo	35.0							Amps
Peak forward surge current, single sine-wave on rated load(JEDEC Method)	IFSM	400.0							Amps
Rating for fusing(1ms <tm<8.3ms)< td=""><td>l²t</td><td colspan="7">660.0</td><td>A²sec</td></tm<8.3ms)<>	l ² t	660.0							A ² sec
Maximum instantaneous forward voltage drop per leg at 17.50 A	VF	1.1							Volts
Maximum DC reverse current Ta=25 ° C at rated DC blocking voltage per leg Ta=125 ° C	lr	5.0 500							μ Α
RMS isolated voltage from case to leads	Viso	2500							Volts
Typical junction capacitance	Сј	300							pF
Typical thermal resistance	Rth-JC	1.4							° C/W
Operating junction and storage temperature range	Tj,Tstg	-55 to +150							° C


Notes: 1. Measured 1MHz and applied reverse voltage of 4.0V DC

RATINGS AND CHARACTERISTIC CURVES






Dimensions in Inches and (millimeters)





Dimensions in Inches and (millimeters)




RATINGS AND CHARACTERISTIC CURVES













RATINGS AND CHARACTERISTIC CURVES











Disclaimer

DACO Semiconductor reserve the right to make modifications, enhancements, improvements, corrections or other changes without further notice to this document and any product described herein.

DACO Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does DACO Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages.

Purchasers is responsible for its products and applications using DACO Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by DACO Semiconductor. "Typical" parameters which may be provided in DACO Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts.

DACO Semiconductor products are not designed, authorized or warranted to be suitable for use in life support, life-critical or safety-critical systems or equipment, nor in applications where failure or malfunction of DACO Semiconductor's product can reasonably be expected to result in personal injury, death or severe property or environmental damage. DACO Semiconductor accept no liability for inclusion and/or use of DACO Semiconductor's products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

Purchasers buy or use DACO Semiconductor products for any such unintended or unauthorized application, Purchasers shall indemnify and hold DACO Semiconductor and its suppliers and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that DACO Semiconductor was negligent regarding the design or manufacture of the part.

No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written permission of DACO Semiconductor Co., Ltd.